



**FIRE & SECURITY**



**Independently Certified to EN50131**


**1 Grade 1**

**2 Grade 2**

**3 Grade 3**

# FLUSH CONTACTS


**FC508 MULTI** **FC508/WH or BR/MULTI/G2**



- Body 20(dia) x 30mm, Face Plate 22 x 33mm
- 4 Terminals
- Selectable Resistors (A, B, D, E, I)
- Microswitch Tamper
- Can be fitted in Normal Double Pole Configuration
- Can be used on Double Doors
- Operating Gap - 12mm

**2**


**FC508 MULTI** **FC508/WH or BR/MULTI/G3**



- Body 20(dia) x 30mm, Face Plate 22 x 33mm
- 4 Terminals
- Selectable Resistors (A, B, D, E, I)
- Microswitch Tamper
- Can be fitted in Normal Double Pole Configuration
- Can be used on Double Doors
- Operating Gap 6mm
- Magnetic Immunity

**3**


**FC503** **FC503/WH or BR/G2**



- 9.5(dia) x 25mm
- 4 Core Pre Wired
- Operating Gap - 15mm
- Double Pole or Pre-restored - see resistor guide for type

**2**

**FC509MT2** **FC509MT2**



- Quick fit metal plated contact
- 25 (dia) x 13 x 57 x 32mm
- 6 Terminal
- Operating Gap - 25mm
- EN50131-2-6 Grade 1 Environmental Class II

**1**

**FC504** **FC504/WH or BR**



- Quick Fit Flush Contact
- Body 19(dia) x 15 - Face plate 35 x 22mm
- 5 Terminal
- Operating Gap - 18mm
- EN50131-2-6 Grade 1 Environmental Class II

**1**


**FC505** **FC505/WH or BR**



- Quick Fit Flush Contact
- Body 19(dia) x 15 - Face plate 35 x 22mm
- 5 Terminal
- Operating Gap - 23mm
- EN50131-2-6 Grade 1 Environmental Class II

**1**


**FC620** **FC620/WH**



- Flush pencil type contact
- 25(dia) x 33mm
- 4 core pre-wired
- Operating Gap - 15mm
- Collar for metal door
- EN50131-2-6 Grade 2 Environmental Class II

**2**

**FS610** **FS610/WH**



- Flush contact with surface adaptor
- 6(dia) x 26mm
- 4 core pre-wired
- Operating Gap - 15mm
- EN50131-2-6 Grade 2 Environmental Class II

**2**

## Resistor Table Guide

Type	Resistor Guide	Switch	Tamper
A	Honeywell, Microtech (Galaxy)	1K Ohms	1K Ohms
B	Scantronic, Cooper, Pyronix PCX, Texecom, Castle-Care Tec G3+	4K7 Ohms	2K2 Ohms
C	Guardall (Network 1 configuration) Two wire only	8K2 Ohms	8K2 Ohms
D	DSC	5K6 Ohms	5K6 Ohms
E	Gardtec	6K8 Ohms	4K7 Ohms

Type	Resistor Guide	Switch	Tamper
F	Bosch, DA Abacus	8K2 Ohms	3K9 Ohms
G	Castle Care-Tec	13K Ohms	1K Ohms
H	Europlex, MDT	2K2 Ohms	2K2 Ohms
I	Pyronix Matrix, GE / Aritech, HKC	4K7 Ohms	4K7 Ohms
J	Texecom	22K Ohms	10K Ohms



FireBrand

2Y-LINK



**CQR Fire & Security**

**125 Pasture Road, Moreton, Wirral, CH46 4TH, UK**



Sales: 0151 606 1000 Tech: 0151 606 6311 [www.cqr.co.uk](http://www.cqr.co.uk)

[info@cqr.co.uk](mailto:info@cqr.co.uk)

