



SAGITTARIUS

SGCP100
Wireless Resettable Call Point



INTRODUCTION

The call point has a resettable plastic element which has the look of glass.

The element once activated can be easily reset by use of a special key.

The same key can be used to remove the device's front cover.

On activation the call point displays a clear visual flag in the window making locating the device easy

A bi-colour (red/green) led provides information regarding the operational modes and condition of power supply

FEATURES & BENEFIT

- Designed to meet the standard EN54-11 and EN54-25
- Bi-directional wireless communication
- Self optimising wireless amplitude and frequency
- Automatic wireless channel hopping
- Fully intelligent
- High reliability and sensitivity
- Utilises standard low cost lithium battery technology, fully monitored
- Immediate transmission of alarm, and fault

Technical Specifications

| | |
|--|---------------|
| Communication range with the VW2W100 or SGW2W (open space) | 600m |
| Operating frequency | 868-870 MHz |
| Modulation type | FSK |
| Operating frequency channels | 7 |
| Primary battery (5 years) | CR123A |
| Secondary battery (2 months) | CR2032A |
| Operating temperature range | -30°C - +55°C |