



FIRE & SECURITY



Independently Certified to EN50131

1 Grade 1

2 Grade 2

3 Grade 3

SURFACE CONTACTS

SC517 MULTI SC517/WH or BR/MULTI/G2



2

- 65 x 13.5 x 13mm
- 4 Terminals
- Selectable Resistors (A, B, D, E, I)
- Microswitch Tamper
- Can be fitted in Normal Double Pole Configuration
- Can be used on Double Doors
- Available White or Brown
- Operating Gap - 15mm


SC517 MULTI SC517/WH or BR/MULTI/G3



3

- 65 x 13.5 x 13mm
- 4 Terminals
- Selectable Resistors (A, B, D, E, I)
- Microswitch Tamper
- Can be fitted in Normal Double Pole Configuration
- Can be used on Double Doors
- Available White or Brown
- Operating Gap - 10mm
- Magnetic Detection


SC570 MULTI SC570/WH or BR/MULTI



2

- 85 x 25 x 20mm
- 6 Terminals
- Selectable Resistors (A, B, D, E, F, H, I)
- Microswitch and Wall Tamper
- Operating Gap - 30mm

SC570 MULTI SC570/WH or BR/MD/MULTI/G3



3

- 85 x 25 x 20mm
- 6 Terminals
- Selectable Resistors (A, B, D, E, F, H, I)
- Microswitch and Wall Tamper
- Operating Gap - 10mm
- Magnetic Detection

SC513 SC513/WH or BR/4C/G2



2

SC513/WH or BR/4C

- 65 x 13.5 x 13mm
- Pre-wired
- Operating Gap - 20mm
- Pre-restored - see resistor guide for type

SC513 SC513/WH or BR/4C/G3



3

SC513/WH or BR/4C

- 65 x 13.5 x 13mm
- Pre-wired
- Operating Gap - 10mm
- Pre-restored - see resistor guide for type
- Magnetic Detection

Resistor Table Guide

Type	Resistor Guide	Switch	Tamper
A	Honeywell, Microtech (Galaxy)	1K Ohms	1K Ohms
B	Scantronic, Cooper, Pyronix PCX, Texecom, Castle-Care Tec G3+	4K7 Ohms	2K2 Ohms
C	Guardall (Network 1 configuration) Two wire only	8K2 Ohms	8K2 Ohms
D	DSC	5K6 Ohms	5K6 Ohms
E	Gardtec	6K8 Ohms	4K7 Ohms

Type	Resistor Guide	Switch	Tamper
F	Bosch, DA Abacus	8K2 Ohms	3K9 Ohms
G	Castle Care-Tec	13K Ohms	1K Ohms
H	Europlex, MDT	2K2 Ohms	2K2 Ohms
I	Pyronix Matrix, GE / Aritech, HKC	4K7 Ohms	4K7 Ohms
J	Texecom	22K Ohms	10K Ohms



FireBrand

2Y-LINK



CQR Fire & Security

125 Pasture Road, Moreton, Wirral, CH46 4TH, UK

Sales: 0151 606 1000 Tech: 0151 606 6311 www.cqr.co.uk

info@cqr.co.uk





FIRE & SECURITY



Independently Certified
to EN50131

1 Grade 1


2 Grade 2

3 Grade 3

SURFACE CONTACTS

SC570

SC570/WH or BR



- 85 x 25 x 20mm
- 6 Terminals
- Cover and Wall Tamper
- Operating Gap - 30mm
- EN50131-2-6 Grade 2
- Environmental Class II

2

SC570

SC570/WH or BR/MD/G3



- 85 x 25 x 20mm
- 6 Terminals
- Cover and Wall Tamper
- Operating Gap - 10mm
- Magnetic Detection
- EN50131-2-6 Grade 3
- Environmental Class II

3

SC517

SC517/WH or BR



- 65 x 13.5 x 13mm
- 5 Terminals
- Operating Gap - 20mm
- EN50131-2-6 Grade 1
- Environmental Class II

1

SC517

SC517/WH or BR/G2



- 65 x 13.5 x 13mm
- 5 Terminals
- Operating Gap - 20mm
- Microswitch Tamper
- EN50131-2-6 Grade 2
- Environmental Class II

2

SC525

SC525/WH or BR/4C



- Patio surface contact
- 38 x 15 x 8mm
- 4 Core pre-wired
- Operating Gap - 20mm
- EN50131-2-6 Grade 2
- Environmental Class II

2

SC555

SC555/WH or BR/



- Alluminium surface contact
- 43 x 17 x 19mm
- 4 Core pre-wired
- Operating Gap - 20mm
- EN50131-2-6 Grade 2
- Environmental Class II

2

SC550

SC550/WH or BR




- Large surface contact
- 85 x 25 x 13mm
- 6 Terminals
- Operating Gap - 30mm
- Leaf spring tamper
- EN50131-2-6 Grade 2
- Environmental Class II

2

FS610

FS610/WH



- Flush contact with surface adaptor
- 6(dia) x 26mm
- 4 core pre-wired
- Operating Gap - 15mm
- EN50131-2-6 Grade 2
- Environmental Class II

2



FireBrand

2Y-LINK



CQR Fire & Security

125 Pasture Road, Moreton, Wirral, CH46 4TH, UK

Sales: 0151 606 1000 Tech: 0151 606 6311 www.cqr.co.uk

info@cqr.co.uk

